CHINNERYS

SOUTHEND • TECHNICAL SPECIFICATIONS • 2026 V8

400 + 20
CAPACITY + GUESTS

AUDIO SYSTEM

HOUSE PRODUCTION

MAIN FOH SYSTEM
- 8 x ASS top cabs - 4 x 10" + 1" (4 per side)
- 4 x EV PX2181 dual 18" subs (2 per side)
- Crown XTI amplification + DBX DriveRack processing

FRONT FILLS / MONITORS
- 2 x KV2 EX10 powered front fills on mono feed
- 7 x D&B MAX 15 monitor wedges available
- Up to 6 separate monitor mixes from FOH
- QSC PLX1602 passive monitor amplification

FOH CONTROL & STAGE I/O
Console Yamaha CL3 - 8 analogue outs + 2 x MY4-DA
Stage I/O Yamaha Rio3224-D1 + Yamaha Tio1608-D1, both stage left
Input patch Analogue inputs 1-48 on the front patch bay

MONITOR RETURNS / IEM ROUTING
Return multi 16-channel analogue returns available stage right
Channels 1-6 FOH monitor sends
Channels 7-12 IEM sends from FOH

PLAYBACK / RECORDING
- Mac mini M4 with Logic for 48-channel Dante recording
- Spotify playback / house music via Mac

MONITOR DESK
- Available on request
- Additional desk + engineer charge applies

MICROPHONE INVENTORY

DYNAMIC / DRUM MICS
- 1 x Audix D6
- 1 x AKG D112
- 1 x Sennheiser e901
- 7 x Shure SM58
- 7 x Shure SM57
- 2 x Sennheiser e609
- 5 x Sennheiser e604

CONDENSERS
- 3 x RODE M5
- 1 x sE Electronics sE1

CHINNERYS

STAGE • LIGHTING • UTILITY INVENTORY

28 x 16 ft
STAGE FOOTPRINT

STAGE & UTILITY

MICROPHONE STANDS
- 12 x K&M 210/9 tall booms
- 2 x generic tall boom stands
- 2 x generic tall straight stands
- 6 x K&M 25900 short booms
- 2 x K&M ultra-short booms

D.I. / HIRES / POWER
- 6 x Radial mono passive DI boxes
- 2 x Radial stereo passive DI boxes
- Radio microphones hired on request as a show cost
- DJ equipment hired on request
- 4 x 16A to 13A Rubber Box-type outputs on stage
- 1 x 32A single-phase supply available on request

LIGHTING SYSTEM

DMX PATCH INCLUDED

HOUSE LIGHTING PACKAGE
- 1 x ChamSys MQ50 lighting controller
- 4 x Chauvet Intimidator Spot 350 moving heads
- 2 x B-Eye fixtures (BEYESTRIP in supplied DMX patch)
- 2 x 200W COB blinders - linked, shared DMX start address
- 16 x HQ RGBW LED PAR cans
- 6 x Elumen8 MQ60 Fresnel LEDs - linked in 3 pairs (3 DMX channels)
- 1 x ADJ Starburst (listed in the DMX patch)
- 1 x ADJ Entour Fazer
- 1 x CAT6 lighting run with 4 DMX universe pick-up points
- Pick-up / CH 1 allocated to house lighting
- DMX patch included on page 4

STAGE DIMENSIONS

MAIN STAGE
Width 28 ft
Depth 16 ft
Height 10 ft
Construction Concrete

RISER / BACKDROP
Drum riser 6 ft x 8 ft
Backdrop bar 7 m wide x 2.5 m high

CHINNERYS

VENUE ACCESS • HOUSE RULES • CONTACTS

2 AM
VENUE LICENCE

ACCESS & PARKING

LOAD-IN / PARKING

- No parking dispensation available. Front-of-venue load-in with a flat ramp directly to stage.
- Zone 1A on-street parking is free after 9pm.
- Vehicles under 2.1 m: use Seaway Car Park.
- Vehicles over 2.1 m: use suitable on-street road bays; Lucy Road is the closest.
- Tour buses: 16A hook-up can be arranged at the front or rear of the venue in advance.

VENUE INFORMATION

CURFEW / NOISE

- Venue licence runs until 2am
- Normal live show finish is around 11pm
- No noise restrictions

AGE RESTRICTION

- All live shows: 14+
- DJ / club nights: strictly 18+

MERCHANDISE

- A couple of suitable merchandise positions are available with a table.
- Merch staff can be provided at additional cost.
- IMPORTANT: no gaffa tape / sticky tape on walls. A charge will apply for damage or residue.

DRESSING ROOM

- 1 x dressing room with direct stage access and private W/C.
- No showers on site. If showers are required, a day room will need to be booked.

PARK INN PALACE	https://www.radissonhotels.com/en-us/hotels/park-inn-southend-on-sea
HOPE HOTEL	https://southendhotel.co.uk/

ADVANCE / CONTACT

EMAIL	PHONE	PRODUCTION
Chinnerys@hotmail.co.uk	01702 613066	Ben or Glyn

CHINNERYS

LIGHTING • DMX PATCH • 31 JUL 2026

U 01

PATCH LIST

DMX FIXTURE PATCH / UNIVERSE 01

Fixture addresses and modes reproduced from the supplied lighting plot. Blank position / hang fields omitted.

HEAD	DMX START	MANUFACTURER	MODEL	MODE
1	01-001	Chauvet DJ	IntSpotLED350	14ch
2	01-015	Chauvet DJ	IntSpotLED350	14ch
3	01-029	Chauvet DJ	IntSpotLED350	14ch
4	01-043	Chauvet DJ	IntSpotLED350	14ch
5	01-153	China	BEYESTRIP	58ch
6	01-211	China	BEYESTRIP	58ch
25	01-400	China	COBBlinder	8ch
26	01-322	ADJ	Starburst	12ch
27	01-319	Elumen8	MP60FresnelWW	1ch
28	01-320	Elumen8	MP60FresnelWW	1ch
29	01-321	Elumen8	MP60FresnelWW	1ch
30	01-512	ADJ	EntourFazer	1ch
31	01-408	HQ Power	FlatPar6x4W	8ch
32	01-416	HQ Power	FlatPar6x4W	8ch
33	01-424	HQ Power	FlatPar6x4W	8ch
34	01-432	HQ Power	FlatPar6x4W	8ch
35	01-440	HQ Power	FlatPar6x4W	8ch
36	01-448	HQ Power	FlatPar6x4W	8ch
37	01-456	HQ Power	FlatPar6x4W	8ch
38	01-464	HQ Power	FlatPar6x4W	8ch
39	01-472	HQ Power	FlatPar6x4W	8ch
40	01-480	HQ Power	FlatPar6x4W	8ch
41	01-488	HQ Power	FlatPar6x4W	8ch
42	01-496	HQ Power	FlatPar6x4W	8ch

ADVANCE NOTE Both 200W COB blinders are linked at DMX start 01-400. The 6 Fresnel LEDs are linked in 3 pairs, with one DMX channel per pair (01-319, 01-320, 01-321). Other inventory items may not appear in this patch.